



**Temposonics**

AN AMPHENOL COMPANY

## Data Sheet

### R-Series V RM5 Analog

Magnetostrictive Linear Position Sensors

- Super shield housing with IP68/IP69 against ingress of dust and water
- Direct analog output, position + speed
- Dual magnet position measurement



THE NEW **V** GENERATION

## MEASURING TECHNOLOGY

The absolute, linear position sensors provided by Tempsonics rely on the company's proprietary magnetostrictive technology, which can determine position with a high level of precision and robustness. Each Tempsonics® position sensor consists of a ferromagnetic waveguide, a position magnet, a strain pulse converter and a supporting electronics. The magnet, connected to the object in motion in the application, generates a magnetic field at its location on the waveguide. A short current pulse is applied to the waveguide. This creates a momentary radial magnetic field and torsional strain on the waveguide. The momentary interaction of the magnetic fields releases a torsional strain pulse that propagates the length of the waveguide. When the ultrasonic wave reaches the beginning of the waveguide it is converted into an electrical signal. Since the speed of the ultrasonic wave in the waveguide is precisely known, the time required to receive the return signal can be converted into a linear position measurement with both high accuracy and repeatability.


## R-SERIES V RM5 Analog

The Tempsonics® R-Series V brings very powerful sensor performance to meet the many demands of your application. The RM5 sensor is the version of the RH5 rod sensor in a protective housing (super shield housing). The main advantages of the RM5 are:




### Protection against corrosion

The housing made of high-quality stainless steel offers very good corrosion resistance. Thus, you can use the R-Series V also in aggressive environments.




### Protection against ingress of dust

The housing protects the internal sensor against penetration of dust. This maintains the sensor's performance even in heavy dust.



### Protection against ingress of water

The housing protects the internal sensor when submerged. This allows you to use the R-Series V even under water.



### Easy and fast replacement

If necessary, the sensor inside the housing can be replaced easily and fast. This saves time and downtime costs.






Fig. 1: Time-of-flight based magnetostrictive position sensing principle

### In addition the R-Series V Analog scores with the following features:



### 2 positions simultaneously

The R-Series V Analog can detect and report the position of up to 2 magnets simultaneously.



### R-Series V Analog

With the R-Series V Analog you can configure the analog output (current/voltage) that it fits best for your application and also adjust it on site with the sensor assistant.

### All settings under control with the sensor assistant for the R-Series V

The TempoLink® smart assistant supports you in setup and diagnostics of the R-Series V. For more information of the assistant please see the data sheet:

- TempoLink® smart assistant  
(Document part number: [552070](#))



## TECHNICAL DATA

Output												
Analog	Voltage: 0...10 / 10...0/-10...+10/+10...-10 VDC (min. controller load > 5 kΩ) Current: 4(0)...20/20...4(0) mA (min./max. load 0/500 Ω)											
Measured output variables	Position for one or two position magnets Position + speed (without direction) or velocity (with direction) for one position magnet Position for one position magnet + temperature inside the sensor electronics housing											
Measurement parameters												
Position measurement												
Null/Span adjustment	100 % of electrical stroke											
Resolution	16 bit (internal resolution 0.1 μm)											
Update time	Stroke length	≤ 200 mm	≤ 350 mm	≤ 1200 mm	≤ 2400 mm	≤ 4800 mm						
	Update time	0.25 ms	0.333 ms	0.5 ms	1.0 ms	2.0 ms						
						≤ 7615 mm						
Linearity deviation <sup>1</sup>	< ±0.01 % F.S. (minimum ±50 μm)											
Repeatability	< ±0.001 % F.S. (minimum ±1 μm)											
Hysteresis	< 4 μm typical											
Temperature coefficient	< 30 ppm/K typical											
Velocity measurement												
Range	0.01...10 m/s or 1...400 in./s											
Deviation	≤ 0.05 %											
Resolution	16 bit (minimum 0.01 mm/s)											
Operating conditions												
Operating temperature	-40...+85 °C (-40...+185 °F)											
Humidity	100 % relative humidity, no condensation											
Ingress protection	IP68 (3 m/180 d)/IP69											
Shock test	100 g/6 ms, IEC standard 60068-2-27											
Vibration test	10 g/10...2000 Hz, IEC 60068-2-6 (excluding resonant frequencies)											
EMC test	Electromagnetic emission according to EN 61000-6-3 Electromagnetic immunity according to EN 61000-6-2 The RM5 sensors fulfill the requirements of the EMC directives 2014/30/EU, UKSI 2016 No. 1091 and TR CU 020/2011											
Operating pressure	350 bar (5076 psi)/700 bar (10,153 psi) peak (at 10 × 1 min) for sensor rod											
Magnet movement velocity	Any											
Design/Material												
Sensor electronics housing	Stainless steel 1.4404 (AISI 316L)											
Sensor flange	Stainless steel 1.4404 (AISI 316L)											
Sensor rod	Stainless steel 1.4404 (AISI 316L)											
RoHS compliance	The used materials are compliant with the requirements of EU Directive 2011/65/EU and EU Regulation 2015/863 as well as UKSI 2022 No. 622											
Stroke length	25...7615 mm (1...299.8 in.)											
Mechanical mounting												
Mounting position	Any											
Mounting instruction	Please consult the technical drawings and the operation manual (document number: <a href="#">552063</a> )											
Electrical connection												
Connection type	Cable outlet											
Operating voltage	+12...30 VDC ±20 % (9.6...36 VDC)											
Power consumption	< 3.25 W											
Dielectric strength	500 VDC (DC ground to machine ground)											
Polarity protection	Up to -36 VDC											
Overvoltage protection	Up to 36 VDC											

## TECHNICAL DRAWING




Fig. 2: Tempsonics® RM5 with ring magnet

## STRUCTURE

The RM5 Analog consists of (Fig. 3)

- 1 Super shield housing
- 2 R-Series V sensor with connector outlet (connection type D34)
- 3 Cable for direct connection to the controller (connection type HXX/RXX/TXX)




Fig. 3: Structure of RM5 Analog

## CONNECTOR WIRING





HXX/RXX/TXX					
Signal + power supply					
Cable	Output	Color	Function		
	1	GY	Position (magnet 1)		
	1	PK	Signal Ground		
2*	YE		Position (magnet 2) or reverse position (magnet 1) or speed or velocity (magnet 1) or temperature inside the sensor electronics housing		
		GN	Signal Ground		
	BN		+12...30 VDC ( $\pm 20\%$ )		
		WH	DC Ground (0 V)		
* order dependent					
For cable type TXX, the extra red & blue wires are not used.					




Fig. 4: Connector wiring HXX/RXX/TXX




## FREQUENTLY ORDERED ACCESSORIES


– Additional options available in our [Accessories Catalog](#)  551444

### Position magnets

			
<b>U-magnet OD33</b> Part no. 251 416-2	<b>Ring magnet OD33</b> Part no. 201 542-2	<b>Ring magnet OD25.4</b> Part no. 400 533	<b>Ring magnet</b> Part no. 402 316
Material: PA ferrite GF20 Weight: Approx. 11 g Surface pressure: Max. 40 N/mm <sup>2</sup> Fastening torque for M4 screws: 1 Nm Operating temperature: -40...+105 °C (-40...+221 °F) Marked version for sensors with internal linearization: Part no. 254 226	Material: PA ferrite GF20 Weight: Approx. 14 g Surface pressure: Max. 40 N/mm <sup>2</sup> Fastening torque for M4 screws: 1 Nm Operating temperature: -40...+105 °C (-40...+221 °F) Marked version for sensors with internal linearization: Part no. 253 620	Material: PA ferrite Weight: Approx. 10 g Surface pressure: Max. 40 N/mm <sup>2</sup> Operating temperature: -40...+105 °C (-40...+221 °F) Marked version for sensors with internal linearization: Part no. 253 621	Material: PA ferrite coated Weight: Approx. 13 g Surface pressure: Max. 20 N/mm <sup>2</sup> Operating temperature: -40...+100 °C (-40...+212 °F)

Position magnet	Magnet spacer	O-rings
		
<b>Block magnet L</b> Part no. 403 448	<b>Magnet spacer</b> Part no. 400 633	<b>O-ring for threaded flange</b> M18x1.5-6g Part no. 401 133
Material: Plastic carrier with hard ferrite magnet Weight: Approx. 20 g Fastening torque for M4 screws: 1 Nm Operating temperature: -40...+75 °C (-40...+167 °F)  This magnet may influence the sensor performance specifications for some applications.	Material: Aluminum Weight: Approx. 5 g Surface pressure: Max. 20 N/mm <sup>2</sup> Fastening torque for M4 screws: 1 Nm	Material: Fluoroelastomer Durometer: 75 ± 5 Shore A Operating temperature: -40...+204 °C (-40...+400 °F)
		Material: Fluoroelastomer Durometer: 75 ± 5 Shore A Operating temperature: -40...+204 °C (-40...+400 °F)

Mounting accessories		
		
<b>Hex jam nut M18x1.5-6g</b> Part no. 500 018	<b>Hex jam nut 3/4"-16 UNF-3A</b> Part no. 500 015	<b>Fixing clip</b> Part no. 561 481
Material: Steel, zinc plated	Material: Steel, zinc plated	Application: Used to secure sensor rods (Ø 10 mm (Ø 0.39 in.)) when using an U-magnet or block magnet Material: Brass, non-magnetic

Cable connector*	Cables		
			
<b>M12 A-coded female connector (4 pin/5 pin), straight Part no. 370 677</b>	<b>PVC cable Part no. 530 032</b>	<b>PUR cable Part no. 530 052</b>	<b>FEP cable Part no. 530 112</b>
<p>Material: GD-Zn, Ni Termination: Screw Contact insert: CuZn Cable Ø: 4...8 mm (0.16...0.31 in.) Wire: 1.5 mm<sup>2</sup> Operating temperature: -30...+85 °C (-22...+185 °F) Ingress protection: IP67 (correctly fitted) Fastening torque: 0.6 Nm</p>			<p>Material: PVC jacket; gray Features: Twisted pair, shielded, flexible Cable Ø: 6 mm (0.23 in.) Cross section: 3 × 2 × 0.14 mm<sup>2</sup> Bending radius: 10 × D (fixed installation) Operating temperature: -40...+105 °C (-40...+221 °F)</p>
<p>Material: PUR jacket; orange Features: Twisted pair, shielded, highly flexible, halogen free, suitable for drag chains, mostly oil &amp; flame resistant Cable Ø: 6.4 mm (0.25 in.) Cross section: 3 × 2 × 0.25 mm<sup>2</sup> Bending radius: 5 × D (fixed installation) Operating temperature: -30...+80 °C (-22...+176 °F)</p>			<p>Material: FEP jacket; black Features: Twisted pair, shielded, flexible, high thermal resistance, mostly oil &amp; acid resistant Cable Ø: 7.6 mm (0.3 in.) Cross section: 4 × 2 × 0.25 mm<sup>2</sup> Bending radius: 8 – 10 × D (fixed installation) Operating temperature: -100...+180 °C (-148...+356 °F)</p>
Cable sets	Programming tools		
			
<b>Cable with M12 A-coded female connector (5 pin), straight – pigtail Part no. 370 673</b>	<b>Hand programmer for analog output Part no. 253 124</b>	<b>Cabinet programmer for analog output Part no. 253 408</b>	<b>TempoLink® kit for Tempsonics® R-Series V Part no. TL-1-0-AD60 (for D60) Part no. TL-1-0-AS00 (for cable outlet) Part no. TL-1-0-AD34 (for D34)</b>
Material: PUR jacket; black Features: Shielded Cable length: 5 m (16.4 ft) Ingress protection: IP67 (correctly fitted) Operating temperature: -25...+80 °C (-13...+176 °F)	Easy teach-in-setups of stroke length and direction on desired zero/span positions. For sensors with 1 magnet.	Features snap-in mounting on standard DIN rail (35 mm). This programmer can be permanently mounted in a control cabinet and includes a program/run switch. For sensors with 1 magnet.	<ul style="list-style-type: none"> <li>• Connect wirelessly via Wi-Fi enabled device or via USB with the diagnostic tool</li> <li>• Simple connectivity to the sensor via 24 VDC power line (permissible cable length: 30 m)</li> <li>• User friendly interface for mobile devices and desktop computers</li> <li>• See data sheet "TempoLink® smart assistant" (document part no.: <a href="#">552070</a>) for further information</li> </ul>

\*/ Follow the manufacturer's mounting instructions

Color of connectors and cable jacket may change. Colors of the cores and technical properties remain unchanged.

Controlling design dimensions are in millimeters and measurements in ( ) are in inches

**Extension cables**



**PVC cable with M12 female connector (6 pin), straight – pigtail**

PVC cable (part no. 530 032) with M12 female connector, straight (part no. 370 677)

Order code:

**K2-A-370677-xxxxyy-530032-0**

(where xxxx = cable length and yy = unit in centimeters "CM" or feet "FT")



**PUR cable with M12 female connector (6 pin), straight – pigtail**

PUR cable (part no. 530 052) with M12 female connector, straight (part no. 370 677)

Order code:

**K2-A-370677-xxxxyy-530052-0**

(where xxxx = cable length and yy = unit in centimeters "CM" or feet "FT")



**FEP cable with M12 female connector (6 pin), straight – pigtail**

FEP cable (part no. 530 112) with M12 female connector, straight (part no. 370 677)


Order code:

**K2-A-370677-xxxxyy-530112-0**

(where xxxx = cable length and yy = unit in centimeters "CM" or feet "FT")

*Color of connectors and cable jacket may change. Colors of the cores and technical properties remain unchanged.*

## ORDER CODE



<b>a</b>	<b>Sensor model</b>	<b>f</b>	<b>Connection type</b>
<b>R</b> <b>M</b> <b>5</b>	Super shield housing	<b>H</b> <b>X</b> <b>X</b>	XX m PUR cable (part no. 530 052) H01...H30 (1...30 m/3...99 ft.) (Note the temperature range of the cable!) See "Frequently ordered accessories" for cable specifications
<b>b</b>	<b>Design</b>	<b>R</b> <b>X</b> <b>X</b>	XX m PVC cable (part no. 530 032) R01...R30 (1...30 m/3...99 ft.) See "Frequently ordered accessories" for cable specifications
<b>M</b>	Threaded flange M18x1.5-6g (standard)	<b>T</b> <b>X</b> <b>X</b>	XX m FEP cable (part no. 530 112) T01...T30 (1...30 m/3...99 ft.) See "Frequently ordered accessories" for cable specifications
<b>S</b>	Threaded flange 3/4"-16 UNF-3A (standard)		Encode in meters if using metric stroke length. Encode in feet if using US customary stroke length.
<b>c</b>	<b>Mechanical options</b>	<b>g</b>	<b>System</b>
<b>A</b>	Standard	<b>1</b>	Standard
<b>d</b>	<b>Stroke length</b>	<b>h</b>	<b>Output</b>
<b>X</b> <b>X</b> <b>X</b> <b>X</b> <b>M</b>	0025...7615 mm	<b>A</b>	Current
	Standard stroke length (mm)	<b>V</b>	Voltage
	Ordering steps		
25... 500 mm	5 mm	<b>i</b>	<b>Function</b>
500... 750 mm	10 mm	<b>1</b>	Position (1 or 2 magnets/outputs)
750...1000 mm	25 mm	<b>2</b>	Position and speed (1 magnet and 2 outputs) Specify the maximum speed value in section <b>I</b>
1000...2500 mm	50 mm	<b>3</b>	Position and velocity (1 magnet and 2 outputs) Specify the maximum velocity value in section <b>I</b>
2500...5000 mm	100 mm	<b>4</b>	Position and reverse position (1 magnet and 2 outputs)
5000...7615 mm	250 mm	<b>5</b>	Position and temperature inside the sensor electronics housing (1 magnet and 2 outputs)
<b>X</b> <b>X</b> <b>X</b> <b>X</b> <b>U</b>	001.0...299.8 in.	<b>6</b>	Differential (2 magnets and 1 output)
	Standard stroke length (in.)		
	Ordering steps		
1... 20 in.	0.2 in.		
20... 30 in.	0.4 in.		
30... 40 in.	1.0 in.		
40...100 in.	2.0 in.		
100...200 in.	4.0 in.		
200...299.8 in.	10.0 in.		
Non-standard stroke lengths are available; must be encoded in 5 mm/0.1 in. increments.		<b>j</b>	<b>Options</b>
<b>e</b>	<b>Number of magnets</b>	<b>0</b>	Standard
<b>0</b> <b>X</b>	01...02 Position(s) (1...2 magnet(s))	<b>3</b>	Over range output mode

k	Output range
0	0...10 VDC or 4...20 mA
1	10...0 VDC or 20...4 mA
2	-10...+10 VDC or 0...20 mA
3	+10...-10 VDC or 20...0 mA
V	0...10 VDC for position, -10...+10 VDC for velocity

I	Max. speed or velocity value
(optional: use when <b>i</b> "Function" is <b>2</b> or <b>3</b> )	
<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	For metric stroke lengths encode speed or velocity in m/s for the values 0.01 to 9.99 m/s (001...999) For US customary stroke lengths encode speed or velocity in inches/s for the values 1 to 400 in./s (001...400)
To get a speed or velocity output of 0.025 m/s or 10 m/s for the R-Series V Analog, enter code (00E) for 0.025 m/s or (A00) for 10.0 m/s in the order code.	

#### NOTICE

- Specify the number of magnets for your application and order the magnets separately.
- The number of magnets is limited by the stroke length. The minimum allowed distance between magnets (i.e. front face of one to the front face of the next one) is 75 mm (3 in.).
- Use magnets of the same type for differential/multi-position measurement.

#### DELIVERY



- Sensor
- O-ring

Accessories have to be ordered separately.

Manuals, Software & 3D Models available at:  
[www.temposonics.com](http://www.temposonics.com)

## GLOSSARY

### A

#### **Analog output**

For a sensor with analog output, the measured value is output as an analog voltage signal or current signal.

### D

#### **Differential**

For differential measurement, the distance between the two position magnets is output as a value.  
(→ multi-position measurement)

### M

#### **Max. speed or velocity value**

For speed or velocity, the output value generated is scaled based on the maximum speed or velocity value indicated in the order code.

#### **Measuring direction**

- Forward: Values increasing from sensor electronics housing to rod end/profile end
- Reverse: Values decreasing from sensor electronics housing to rod end/profile end

#### **Multi-position measurement**

During the measurement cycle, the positions of every magnet on the sensor are simultaneously reported. The velocity or speed is continuously calculated based on these changing position values as the magnets are moved.

### O

#### **Over range output mode**

When enabled this mode allows the position output values to continue to increase or decrease when the magnet travels beyond the active stroke range.

### R

#### **Resolution**

The sensor precisely measures time to provide the position measurement. For the analog output the measured time value is converted into an analog voltage signal or current signal using a high-performance **Digital to Analog Converter (DAC)** having 16 bits of resolution.

### S

#### **Speed**

The output value for speed indicates how fast the position magnet is being moved, independent of the measuring direction. (→ Velocity)

### T

#### **Temperature inside the sensor electronics housing**

The temperature inside the sensor electronics housing is reported as an analog voltage signal or current signal. For each output range, the 0 % output value has the factory default setpoint at -40 °C, and the 100 % output value has the default setpoint at +100 °C.

Note: A dedicated temperature chip is used for the output signal and its values may vary from those reported on the **TempoLink®** application screen.

### V

#### **Velocity**

The output value for velocity indicates how fast the position magnet is being moved, and in which direction. (→ Speed)



# Tempsonics

AN AMPHENOL COMPANY

**UNITED STATES** 3001 Sheldon Drive  
**Tempsonics, LLC** Cary, N.C. 27513  
Americas & APAC Region Phone: +1 919 677-0100  
E-mail: info.us@tempsonics.com

**GERMANY** Auf dem Schüffel 9  
**Tempsonics** 58513 Lüdenscheid  
**GmbH & Co. KG** Phone: +49 2351 9587-0  
EMEA Region & India E-mail: info.de@tempsonics.com

**ITALY** Phone: +39 030 988 3819  
Branch Office E-mail: info.it@tempsonics.com

**FRANCE** Phone: +33 6 14 060 728  
Branch Office E-mail: info.fr@tempsonics.com

**UK** Phone: +44 79 21 83 05 86  
Branch Office E-mail: info.uk@tempsonics.com

**SCANDINAVIA** Phone: +46 70 29 91 281  
Branch Office E-mail: info.sca@tempsonics.com

**CHINA** Phone: +86 21 3405 7850  
Branch Office E-mail: info.cn@tempsonics.com

**JAPAN** Phone: +81 3 6416 1063  
Branch Office E-mail: info.jp@tempsonics.com

**Document Part Number:**  
552114 Revision A (EN) 02/2026



## tempsonics.com

© 2026 Tempsonics, LLC – all rights reserved. Tempsonics, LLC and Tempsonics GmbH & Co. KG are subsidiaries of Amphenol Corporation. Except for any third party marks for which attribution is provided herein, the company names and product names used in this document may be the registered trademarks or unregistered trademarks of Tempsonics, LLC or Tempsonics GmbH & Co. KG. Detailed trademark ownership information is available at [www.tempsonics.com/trademarkownership](http://www.tempsonics.com/trademarkownership).